

# LA-437 ListenTALK Line/Headset Mix Cable

## QUICK START GUIDE



Connect the LA-437 cable to the ListenTALK Transceiver - connect the 3.5 mm TRRS plug into the 3.5 mm connector on the top of the ListenTALK labeled with the Headset logo.


Connect the 3.5 mm plug from the Headset into the LA-437 cable labeled "Headset"



Connect the 3.5 mm plug from the Line Input Device into the LA-437 Cable labeled "Audio Input"



Adjust the reduced Line Level Audio Mix by increasing or decreasing the Audio Mix control. Clockwise increases the level while counter-clockwise decreases the level



The LA-437 Line/Headset Mix Cable allows a ListenTALK (LK-1) with a Leader Clip, to connect a Line Input and Headset. This allows the leader to alternate between mic-audio and playback of music or an audio file.

The cable has a push-button and slide switch which allows the leader to choose different modes of operation:

push button



mode slide switch



Select Cable Mode 1, 2, or 3. Mode 1 is the factory default position.

- Mode 1: allows a leader to switch between their microphone or a line level audio input.
- Mode 2: allows a leader to switch between a line level audio input or a mix of their microphone with reduced line level audio input.
- Mode 3: allows a leader to switch between their microphone or a mix of their microphone with reduced line level audio input.

Mode	Button	Function
1	Latched (Pressed)	Headset Mic Audio
	Released (Not Pressed)	Line Level Audio
2	Latched (Pressed)	Mix, Headset Mic with reduced Line Level Audio Input
	Released (Not Pressed)	Line Level Audio
3	Latched (Pressed)	Headset Mic Audio
	Released (Not Pressed)	Mix, Headset Mic with reduced Line Level Audio Input